

# Growatt ShineLink-X

- Cable free, easy installation
- Dynamic IP, plug and play
- Communication distance up to 120m
- Support up to 8 devices
- Built-in memory for up to one month of data
- Online monitoring and maintenance



P O W E R  
- I N G O  
T O M O -  
R R O W O



Datasheet	ShineLink-X	
<b>Communication Interface</b>		
RF433		Yes
RF433(No barrier wall)		Up to 120 m
RF433(two walls blocking)		20 m
<b>Power Supply</b>		
Power consumption		<2W standby, <5W peak
Voltage range		196V~250V
Frequency		50/60Hz
<b>General Specifications</b>		
Dimensions(L/W/H)		105/85/26mm
Weight		< 1kg
Mounting options		Tabletop/wall-mount
Protection degree		IP30
Display		LED
Ambient temperature range		-20 to 65 °C
Humidity		0-95% (non condensing)
<b>Features</b>		
Remote firmware upgrade		Yes
Max. number of devices to monitor		8(RF433)
Warranty		1 years
CE		